

# MEF

## Technical Specification

### MEF 7.1.1

## Technical Corrections to MEF 7.1

**July 2010**

## Disclaimer

The information in this publication is freely available for reproduction and use by any recipient and is believed to be accurate as of its publication date. Such information is subject to change without notice and the Metro Ethernet Forum (MEF) is not responsible for any errors. The MEF does not assume responsibility to update or correct any information in this publication. No representation or warranty, expressed or implied, is made by the MEF concerning the completeness, accuracy, or applicability of any information contained herein and no liability of any kind shall be assumed by the MEF as a result of reliance upon such information.

The information contained herein is intended to be used without modification by the recipient or user of this document. The MEF is not responsible or liable for any modifications to this document made by any other party.

The receipt or any use of this document or its contents does not in any way create, by implication or otherwise:

- a) any express or implied license or right to or under any patent, copyright, trademark or trade secret rights held or claimed by any MEF member company which are or may be associated with the ideas, techniques, concepts or expressions contained herein; nor
- b) any warranty or representation that any MEF member companies will announce any product(s) and/or service(s) related thereto, or if such announcements are made, that such announced product(s) and/or service(s) embody any or all of the ideas, technologies, or concepts contained herein; nor
- c) any form of relationship between any MEF member companies and the recipient or user of this document.

Implementation or use of specific Metro Ethernet standards or recommendations and MEF specifications will be voluntary, and no company shall be obliged to implement them by virtue of participation in the Metro Ethernet Forum. The MEF is a non-profit international organization accelerating industry cooperation on Metro Ethernet technology. The MEF does not, expressly or otherwise, endorse or promote any specific products or services.

© The Metro Ethernet Forum 2010. All Rights Reserved.

---

**Table of Contents**

<b>1.</b>	<b>Change Highlighting</b> .....	<b>1</b>
<b>2.</b>	<b>Correction #1: Section 9.4.1.4 EthOamPerfMonCfg</b> .....	<b>1</b>
<b>3.</b>	<b>Correction #2: Section 9.3.2.1 EthOamLbCfg</b> .....	<b>2</b>
<b>4.</b>	<b>Correction #3: Appendix IV Protocol Specific SNMP MIB Object Mappings</b> .....	<b>3</b>
<b>5.</b>	<b>Correction #4: Appendix III Data Type Definitions</b> .....	<b>3</b>
<b>6.</b>	<b>References</b> .....	<b>4</b>

## 1. Change Highlighting

For ease in reviewing and editing, changes can be indicated under the “new text section” by using [blue underline](#) for new inserted text, and ~~red strikethrough~~ for deleted text.

## 2. Correction #1: Section 9.4.1.4 EthOamPerfMonCfg

OLD TEXT:

<b>priority</b>	This attribute specifies the priority of frames with Performance Monitoring OAM message information. The value 'true' indicates frames are eligible to be discarded. The value 'false' indicates frames are not eligible to be discarded.	PriorityType	Highest allowed on the bridge port	M, R/W
<b>vlanPcp</b>	This attribute specifies a configurable VLAN PCP for Performance Monitoring OAM message frame transmission. The default configured VLAN PCP should correspond to the CoS which yields the lowest frame delay performance for this EVC. This is not applicable if the MEG is untagged.	Integer		M, R/W

NEW TEXT:

<b>priority</b>	This attribute specifies the priority of frames with Performance Monitoring OAM message information. <del>The value 'true' indicates frames are eligible to be discarded. The value 'false' indicates frames are not eligible to be discarded.</del>	PriorityType	Highest allowed on the bridge port	M, R/W
-----------------	--	--------------	------------------------------------	--------

<del>vlanPcp</del>	<del>This attribute specifies a configurable VLAN PCP for Performance Monitoring OAM message frame transmission. The default configured VLAN PCP should correspond to the CoS which yields the lowest frame delay performance for this EVC. This is not applicable if the MEG is untagged.</del>	<del>Integer</del>	<del>-</del>	<del>M, R/W</del>
--------------------	--	--------------------	--------------	-------------------

### 3. Correction #2: Section 9.3.2.1 EthOamLbCfg

#### OLD TEXT:

<b>multicastEnabled</b>	This attribute specifies whether a MEP uses unicast or multicast to send the ETH-LM messages (LBM/LBR). A MEP can send ETH-LM messages to unicast or multicast MAC addresses. The value 'true' indicates multicast is enabled. The value 'false' indicates unicast is enabled.	Boolean	false	O, R/W
-------------------------	--	---------	-------	--------

#### NEW TEXT:

<b>multicastEnabled</b>	This attribute specifies whether a MEP uses unicast or multicast to send the ETH-LMB messages (LBM/LBR). A MEP can send ETH-LMB messages to unicast or multicast MAC addresses. The value 'true' indicates multicast is enabled. The value 'false' indicates unicast is enabled.	Boolean	false	O, R/W
-------------------------	--	---------	-------	--------

## 4. Correction #3: Appendix IV Protocol Specific SNMP MIB Object Mappings

The change below is found in the EthOamCcCfg section of the table.

OLD TEXT:

faultAlarmTime		
faultAlarmResetTime		

NEW TEXT:

faultAlarmTime	<a href="#">dot1agCfmMepFngAlarmTime</a>	
faultAlarmResetTime	<a href="#">dot1agCfmMepFngResetTime</a>	

The change below is found in the EthOamLbCfg section of the table.

OLD TEXT:

lbmMsgStatus		
--------------	--	--

NEW TEXT:

lbmMsgStatus	<a href="#">dot1agCfmMepTransmitLbmStatus</a>	
--------------	---	--

The change below is found in the EthOamLbStats section of the table.

OLD TEXT:

firstLbmTransId		
-----------------	--	--

NEW TEXT:

firstLbmTransId	<a href="#">dot1agCfmMepTransmitLbmSeqNumber</a>	
-----------------	--	--

## 5. Correction #4: Appendix III Data Type Definitions

OLD TEXT:

PriorityType	This data type represents a frame priority and is represented as an integer in the range 0..7.			Y.1731
--------------	--	--	--	--------

NEW TEXT:

PriorityType	This data type represents a frame priority <del>and is represented as an integer in the range 0..7.</del>	<u>Unsigned Integer</u>	<u>0..7</u>	<del>Y.1731</del> <u>IEEE 802.1ap</u>
--------------	---	-------------------------	-------------	---------------------------------------

## 6. References

- [1] Metro Ethernet Forum, MEF 7.1, Phase 2 EMS-NMS Information Model, October 2009.